

APPLICATION FOR UNITED STATES LETTERS PATENT

FOR

Method and Apparatus for Color Correction

Inventors: Randy Ubillos
Eric Graves

Prepared by:
Stattler, Johansen & Adeli LLP
P.O. Box 51860
Palo Alto, California 94303-0728
PHONE: 650.934.0470 x101
FAX: 650.934.0475

"Express Mail" mailing label number _____

Date of Deposit _____

I hereby certify that this paper or fee is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to the Assistant Commissioner for Patents, Washington, DC 20231.

(Typed or printed name of person mailing paper or fee)

(Signature of person mailing paper or fee)

10005203 120304

Method and Apparatus for Color Correction

FIELD OF THE INVENTION

5 The present invention relates to the field of digital image processing. In particular the present invention discloses a graphical user interface and methods for performing color correction and color keying.

BACKGROUND OF THE INVENTION

10 Recent advances in video processing technologies have led to a surge in popularity of new video processing applications that make powerful video editing capabilities available to a wide base of users. Typically, video processing applications allow users to download and upload video and audio segments, as well as edit and
15 manipulate these segments for producing a cohesive video or movie.

20 In performing such tasks, video processing applications often use a video capture card to capture and store video segments onto the hard drive of a computer system. Video capture cards typically employ a coder/decoder (also called a "CODEC") to compress the video with a compression standard such as Motion-JPEG, DV, MPEG-1, MPEG-2, etc. Many digital video storage formats store pixel data in a luminance and chrominance colorspace often referred to Y/Cr/Cb (also referred to as YUV). In a luminance and chrominance colorspace three components are stored for each pixel: one for luminance (Y) and two for color information (Cr and Cb). Most computer display
25 systems store pixel information in an RGB format that also contains three components

per pixel, one each for the Red (R), Green (G), and Blue (B) portions of the color. Pixel information stored in either YUV or RGB format can be converted to the other format using straightforward matrix mathematics.

5 In the DV (digital video) storage format, storage is typically accomplished with an 8-bit luminance (Y) value for each pixel. 8 bits allows luminance (Y) values ranging from 0 through 255. In 8-bit digital video, black is typically encoded at $Y = 16$ and white is encoded at $Y = 235$. The luminance values from 1 to 15, referred to as footroom, and 236 to 254, referred to as headroom, are used to accommodate ringing and overshoot in a signal. Industry standard equations (such as those specified by Rec. ITU R BT-601) can convert 8-bit RGB encoded images with RGB values ranging from 0 to 255 into YUV encoded images with luminance (Y) values ranging from 16 to 235. Most software DV CODECs follow this mapping so that a user may translate, say, naturalistic computer pictures into quality video.

10 However, there are several phenomena which may contribute to degradation or compromising of the dynamic range of given colors in a resulting video segment. For example, difficulties often arise, for example, because cameras can often capture values that are superwhite (values resulting from specular reflections, sun, or bright lights, clouds or white walls). Superwhite values may exceed the nominal white value of 235 as registered on a waveform monitor, where these whites may peak at 100 IRE (NTSC) which is the brightest value allowable on a broadcast RF modulator. In the YUV space, the Y values range from 16 to 235; but on a waveform monitor, whites can be seen to range from 100 IRE to almost 110 IRE, all of which represent illegal values (e.g., Y values above 235), and are accordingly clipped to 235 by a CODEC when

converting to RGB, thereby compromising the dynamic range of at least the white value in a given digital image.

Typically, users may attempt to mitigate such value degradation by
5 employing color correction of the RGB space. A problem arises, however, because color
correction, still yield only a limited amount of headroom for colors (such as superwhite),
and also require extensive operations cycles, execution time, and memory access in
computer systems that support digital video processing applications. Inherent in such a
problem is the need for rendering, where editing is translated and stored on the hard drive
10 a computer system supporting a given video image processing application. Even recently
developed "real time" systems still need to go back to rendering in cases where a user
simultaneously color corrects, adds filters, effects, and superimposes graphics, even for a
high end real time system, the capacity will be overwhelmed and the real time
performance will be compromised. As such, there are still deficiencies not addressed by
15 recent advances in video processing, which in particular concerns the limited overhead on
color values and a less expensive approach to color correction.

SUMMARY OF THE INVENTION

A graphical user interface for performing color correction and methods for implementing the color correction are disclosed. The graphical user interface allows a user to adjust the colorspace of the pixels in the image. In one embodiment, a color adjustment pad allows the user to push the pixels from a particular luminance level a desired magnitude towards a desired hue. Pixels from other luminance levels are affected proportionally. The graphical user interface further allows a user to adjust the luminance of the pixels in the image. A luminance adjustment slider allows the user to adjust the luminance of pixels from a selected luminance level by a relative amount. Pixels from other luminance levels have their luminance are affected in a manner proportional to a difference between the selected luminance level value and the luminance value of the other pixel.

Other objects, features, and advantages of present invention will be apparent from the company drawings and from the following detailed description.

BRIEF DESCRIPTION OF THE DRAWINGS

The objects, features, and advantages of the present invention will be apparent to one skilled in the art, in view of the following detailed description in which:

5

Figure 1(a) illustrates a conceptual diagram of a three-dimensional colorspace defined in the luminance (Y) and chrominance (UV) format known as a YUV format.

10

Figure 1(b) illustrates a conceptual diagram of a three-dimensional colorspace of **Figure 1(a)** defined in an alternate hue (H), saturation (S), and luminance (Y) format.

15

Figure 2 illustrates one embodiment of a graphical user interface for a color correction control system of the present invention.

Figure 3(a) illustrates a compliant video frame in the canvas window.

20

Figure 3(b) illustrates a subsequent video frame in the canvas window with all the pixels close to an allowable maximum highlighted with zebra striping.

25

Figure 3(c) illustrates a subsequent video frame in the canvas window with all the pixels close to an allowable maximum highlighted with a first zebra striping and all the pixels exceeding the allowable maximum highlighted with a second zebra striping.

Figure 4 illustrates one embodiment of a graphical user interface for the color correction window **230** of the color correction control system in **Figure 2**.

5 **Figure 5** illustrates a white luminance plane, a mids luminance plane, and a blacks luminance plane in the colorspace of **Figures 1(a)** and **1(b)**.

Figures 6(a) illustrates the effect of moving the white luminance plane of the cylindrical colorspace representation to the right.

10 **Figures 6(b)** illustrates the effect of moving the black luminance plane of the cylindrical colorspace representation to the right.

15 **Figure 7** illustrates the effect of moving the mids luminance plane on the cylindrical colorspace representation to the right.

Figure 8 illustrates the effect of moving the mids luminance plane to the right on a cylindrical colorspace already modified as illustrated in **Figure 6(a)**.

20 **Figure 9** illustrates a first alternate embodiment of a graphical user interface for the color correction window **230** of the color correction control system in **Figure 2**.

Figure 10 illustrates a second alternate embodiment of a graphical user interface for the color correction window **230** of the color correction control system in **Figure 2**.

Figure 11 illustrates a flow diagram of one color correction implementation that performs color correction using look-up tables recomputed based upon user input from a graphical user interface.

Figure 12 illustrates a flow diagram describing pixel remapping using the color correction system of the present invention.

Figure 13 illustrates a graphical representation of an exemplary range of potential transitions for the different pixel luminance input versus pixel luminance output relationships within a lookup table for luminance correction.

Figures 14(a) to 14(g) illustrates graphical representations of the various input versus output relationships within a lookup table for luminance correction within the inventive system, as well as the control points of the Bezier curve which describes the M control modifications within the look-up table.

Figure 15 illustrates an unmodified cylindrical colorspace representation where the white (W), mid (M), and black (B) luminance planes are all physically centered on the $C_b = 0, C_r = 0$ axis, and where none of the values $U_w, V_w, U_M, V_M, U_b, V_b$ have been modified.

Figure 16 illustrates a cylindrical colorspace representation where the white (W), mid (M), and black (B) luminance planes have been pushed an equal amount to reflect changed Cb and Cr values regardless of luminance.

5 **Figure 17** illustrates a cylindrical colorspace representation where the white (W), mid (M), and black (B) luminance planes have been pushed such that Cb has been pushed negative at *M*, but *B* and *W* remain the same.

10 **Figure 18** illustrates the abstract control points that form the basis for an exemplary Bezier curve function called “gMidRamp”.

Figure 19 illustrates the gMidRamp function that can be used to calculate a look up table for Cb and Cr across the various luminance levels.

15 **Figure 20** illustrates the look up table that provides a Cb offset amount for a given luminance input, as a result of the application of the gMidRamp function to the modified colorspace of **Figure 17**.

20 **Figure 21** illustrates another example of a modified cylindrical colorspace representation where Cb and Cr have been pushed at *M* and *W*, but *B* remains the same.

Figure 22 illustrates the look up table that provides an offset amount for a given luminance input, as a result of the application of the gMidRamp function to the Cb example taken from the specific example in **Fig. 21**.

25

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

A method and user interface for performing color correction is disclosed. In the following description, for purposes of explanation, specific nomenclature is set forth to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that these specific details are not required in order to practice the present invention. For example, the present invention has been described with reference to Bezier curves. However, the same techniques can easily be applied with other types of curved functions.

Digital Video and Colorspaces

Digital video pixel information is commonly stored in a three component luminance and chrominance format. For example, both the MPEG-1 and MPEG-2 digital video standards encode pixel data with three component luminance and chrominance format.

The luminance specifies the brightness of a pixel. Luminance ranges from pure black to pure white. Luminance is typically expressed in a single component Y value. The chrominance specifies the color of a pixel and is stored as two component values Cr and Cb (that are also referred to as U and V values). One reason that digital video is stored in a luminance and chrominance format is that human vision is much more sensitive to luminance information than chrominance information such that separate chrominance information can be more heavily compressed without significantly detectable image degradation.

Computer display systems generally represent pixel information in a three component RGB format wherein the three components specify the amount of Red (R), Green (G), and Blue (B) required to represent a pixel. Pixel information stored in either RGB format or YUV format can easily be converted to the other format using simple matrix math.

Figure 1(a) illustrates a conceptual diagram of a three-dimensional colorspace defined in the luminance (Y) and chrominance (UV) YUV format. The two part UV chrominance value is not intuitive to humans. Thus, the colorspace often defined in an alternative hue (H), saturation (S), and luminance (Y) format.

Figure 1(b) illustrates an alternate interpretation of the three-dimensional colorspace in **Figure 1(a)**. The colorspace of **Figure 1(b)** is defined in terms of luminance (Y), hue (H), and saturation (S).

The luminance (Y) value continues to represent the brightness of a pixel. Luminance (Y) is represented as a vertical coordinate along the vertical axis of the cylinder of the cylindrical colorspace of **Figure 1(b)**.

The hue (H) represents a particular color value. Hue is represented as an angle from the center of the cylinder of the cylindrical colorspace of **Figure 1(b)**. Hue is often specified on a common color wheel.

Saturation (S) refers to the depth or intensity of a pixel's color (hue). In other words, how strong the color is relative to an unsaturated white/gray/black of the same luminance level. For example, a deep red has a high level of saturation (mostly pure red with little white) and a pinkish red is only lightly saturated (less pure red and a higher level of white). Saturation is represented in the colorspace of **Figure 1(b)** as a distance along a vector defined by the hue (H) angle.

Color Correction

Film and television feature productions generally go through three phases: pre-production, production, and post-production. The pre-production phase is when the script is created, the actors are cast, and the sets are built. During production phase, the actual film is shot or the videotape is recorded using the actors and sets. Finally, during the post-production, the film or video tapes is edited together, the sound is edited, music is added, special effects are added, and the film or video tape images are adjusted.

As part of the post-production process, the images from many films and television shows go through a process of "color correction." The process of color correction is used to fix color problems that occur during the filming or videotape production.

Professional colorists refer to primary, secondary, and tertiary color correction. Primary color correction involves fixing the basic color balance of an image to make it look correct with true color representation. Primary color correction problems include incorrect color casting from bad lighting, color problems caused by color filters,

and improper exposure. Secondary color correction problems are caused by mismatched colors for related scenes shot at different times or with different lighting.

Tertiary color correction is actually color enhancement such as making a scene darker to enhance a particular mood. Tertiary color correction is also used to perform certain special effects. For example, the director or editor may wish to change the color of specific objects in a scene. For example, the director or editor may change the color of clothing worn by a particular character. The director may change the eye color of characters such as the distinctive blue eyes in the feature film "Dune."

A Color Correction System

The present invention introduces a new color correction system that allows post-production specialists to have a wide latitude of control over the colors in series of images. The color correction system uses a highly intuitive graphical user interface such that post-production specialists can quickly learn the color correction system and professionally apply its features.

Figure 2 illustrates one embodiment of a graphical user interface for a color correction control system of the present invention. In the graphical user interface of **Figure 2**, there are three different windows for presenting information.

Image Canvas Window

A first window **210** is a "canvas" window that displays the video or other images that are being adjusted with the color correction system. In a preferred

embodiment, the canvas window **210** includes novel feedback systems that provide more information than just the image.

Images may contain pixels that exceed a maximum luminance value allowed for broadcast material. Thus, it would be desirable to be able to identify and locate pixels that exceed this maximum allowed luminance value. In one embodiment, the canvas window **210** can be placed into a luminance test mode. When in the luminance test mode, the color correction system tests the all the pixels in an image to determine if the luminance of each pixel is close to or above an acceptable luminance threshold value. An example of luminance test mode will be described with reference to **Figures 3(a) to 3(c)**.

Figures 3(a) illustrates a canvas window video frame **310** that is tracking a ski jumper that will soon pass by the sun **320** that is currently not in the video frame. The sun emits so much light that it can easily cause image pixels having luminance values that are out of range. Referring to **Figure 3(a)**, since the skier is not yet close enough to the sun, all the pixels are currently within the luminance limit. Thus, when all the pixels are within the maximum luminance value, the canvas window video frame **310** may simply display an indication such as the "OK" indication **350** that indicates that the image is compliant with the luminance restrictions.

Referring to **Figure 3(b)**, as the skier comes closer to the sun, some of the pixels in a halo around the sun come very close to the maximum luminance value allowed for broadcast material. In one embodiment, "very close" is defined as within 10% maximum luminance value allowed for broadcast material. To warn the user about this,

the luminance test mode displays a warning indication 360 in the canvas window video frame 310. Furthermore, the luminance test mode highlights the pixels 331 very close to the maximum luminance value. In one embodiment, the pixels are “zebra striped” with green stripes. Note that the zebra striping allows the underlying image to remain visible.

5

Finally, referring to **Figure 3(c)**, the skier is close to the sun such that some of the pixels from a halo around the sun come exceed the maximum luminance value allowed for broadcast material. To alert the user about the “illegal” pixels, the luminance test mode displays a violation indication 370 in the canvas window video frame 310. Furthermore, the luminance test mode highlights the pixels 332 very close to the maximum luminance value and the noncompliant pixels 342 that exceed the maximum luminance value. In one embodiment, the pixels close to the maximum luminance value are zebra striped with green stripes and the pixels exceeding the maximum luminance value are zebra striped with red stripes.

10

15

In alternate embodiments, the luminance test mode may display pixels “close” (within 20%) with green zebra striping, “very close” (within 10%) with yellow zebra striping, and exceeding the maximum luminance value with red zebra striping. Furthermore, in one embodiment the canvas window video frame implements a saturation test mode. When in the saturation test mode, the pixels that exceed the maximum allowed color stripes are highlighted with zebra striping. In a preferred embodiment, the user may activate the luminance test mode and the saturation test mode simultaneously such that the user can locate over saturated pixels and pixels that exceed the maximum allowed luminance value at the same time.

20

25

Workbench Scopes Window

A second window **220** is a “workbench” window that displays a number of commonly used scopes for video editing. The workbench window **220** may include scopes such as a waveform monitor, a vectorscope, and a luminosity histogram as is well known in the art. Other useful graphs may be created or subsequently added at a later date. The combination of the canvas window **210** and the workbench window **220** provide feedback to the user.

Color Correction Tools Window

The third window **230** is a color correction interface window that contains tools for performing color correction. The color correction interface window **230** comprises a graphical user interface containing several different color correction tools for performing color correction on the images in the canvas window **210**. The graphical user interface containing several different color correction tools for performing color correction and the methods that implement those color correction tools are one of the primary focuses of this document.

A Color Correction Graphical User Interface

Figure 4 illustrates one embodiment of a graphical user interface for the color correction window **230** of the present invention. Other embodiments will be described but practicing the invention does not require implementing all the features of one particular embodiment.

Color Plane Adjustment Pads

In the color correction window 230 embodiment of **Figure 4**, there are three different color adjustment pads **430**, **420**, and **410**. Each color adjustment pad displays the spectrum of hues around the perimeter. The primary and secondary colors of the spectrum are labeled on the color adjustment pad spectrum as Red (R), Magenta (Mg), Blue (B), Cyan (Cy), Green (G), and Yellow (Yl). Different saturation levels are displayed for each hue with zero saturation (white) in the center. A hatch mark **431**, **421**, and **411** specifies the normal flesh tone hue for the different color adjustment pads **430**, **420**, and **410**, respectively.

The color adjustment pads **430**, **420**, and **410** allow the user to adjust the meaning of “white”, “gray”, and “black” respectively by shifting the center toward a particular hue. Specifically, a user may use a cursor control device to draw a vector from the center **431**, **421**, and **411** of a color adjustment pad toward a particular hue (angle) for a specified distance (magnitude). The color correction then adjusts all the colors accordingly. In a preferred embodiment, the controls produce relative adjustments.

The three different color adjustment pads **410**, **420**, and **430** correspond to constant luminance planes in the three-dimensional colorspace illustrated in **Figure 5**.

Specifically, whites color adjustment pad **430** corresponds to whites luminance plane **530**, mids (middle) color adjustment pad **420** corresponds to a mids (middle) luminance plane **520**, and blacks color adjustment pad **410** corresponds to blacks luminance plane **510**. The three different color adjustment pads **430**, **420**, and **410** allow a user to adjust the colors of pixels havening the luminance level of the corresponding luminance plane **530**, **520**, and **510**, respectively.

Each color adjustment pad **410**, **420**, and **430** includes an associated reset button **417**, **427**, and **437**, respectively. The reset button resets the color balance to the default (no adjustment) state.

5

Each color adjustment pad **410**, **420**, and **430** also includes an eyedropper button **415**, **425**, and **435**, respectively. The eyedropper button allows the user to select a color from the image and define that selected color as the center (unsaturated) value of the associated luminance plane. In this manner, a user may perform post-production white balancing by selecting a colored pixel from an object known to be white in an image.

10

When an adjustment is made for a particular luminance level, other luminance levels are affected as well. When the whites color adjustment pad **430** or the blacks color adjustment pad **410** is used to adjust the whites luminance plane **530** or blacks luminance plane **510**, respectively, all the other luminance planes are adjusted proportionally according to their distances from the adjusted luminance plane. In one embodiment, an adjustment to the whites luminance plane **530** or blacks luminance plane **510** causes the other luminance planes to be adjusted depending on how close those planes are to the adjusted luminance plane. When the mids color adjustment pad **420** is used to adjust the mids luminance plane **520**, then the other luminance planes are also adjusted. However, in one embodiment, an adjustment to the mids luminance plane **520** causes the other luminance planes to be adjusted according to a curve depending on how close those planes are to the adjusted mids luminance plane **520**.

15

20

25

Color Plane Adjustment Examples

Referring to **Figure 4**, if the user moves the center of the whites color adjustment pad **430** to the right, the pixels of the high luminance level plane **530** are adjusted toward the blue (B) hue and lower luminance level planes are adjusted proportionally. Specifically, **Figure 6(a)** illustrates how the three-dimensional colorspace is adjusted when the user moves the center of the whites color adjustment pad **430** to the right by an amount of ΔX . Note that the mids luminance plane **620** is moved over half as much $((\Delta X)/2)$ as the whites luminance level plane **630** and that the blacks luminance level plane **610** is not adjusted at all. Note that the luminance axis Y now extends upward at an angle into the colorspace.

Similarly, if the user moves the center of the blacks color adjustment pad **410** to the right, the pixels of the blacks luminance level plane are adjusted toward the blue (B) hue and higher luminance level planes are adjusted proportionally. Specifically, **Figure 6(b)** illustrates how the three-dimensional colorspace is adjusted when the user moves the center of the blacks color adjustment pad **410** to the right by an amount ΔX . Again, the mids luminance plane **670** is moved over half as much $((\Delta X)/2)$ as the blacks luminance plane **660** and the whites luminance level plane **680** remains stationary.

If the user moves the mids (middle) color adjustment pad **420**, the system moves colors of the mids luminance plane **520** accordingly. The other luminance planes are also moved, but by an amount specified by a curve. Specifically, **Figure 7** illustrates how the three-dimensional colorspace is adjusted when the user moves the center of the mids color adjustment pad **420** to the right by an amount ΔX . As illustrated in **Figure 7**, the mids luminance plane **720** is moved over by the amount ΔX specified by the user.

The other luminance level planes are adjusted in the same direction by an amount specified by a combination of ΔX and curve 750. In one embodiment, curve 750 is defined as a well-known Bezier's curve. Note that the luminance axis Y is now curved.

5 The movements of the three different color adjustment pads 430, 420, and 410 may be combined to create different colorspace adjustments. For example, the user may first adjust the whites luminance level plane 530 to right by ΔX using the whites color adjustment pad 430 to produce the adjusted colorspace illustrated in Figure 6a. The user may then subsequently adjust the mids luminance plane 520 using the mids color adjustment pad 420. Figure 8 illustrates how the three-dimensional colorspace is appears after the user moves the center of the mids color adjustment pad 420 to the right by an amount of $\Delta X'$. Note that the mids luminance level plan 892 has been shifted by $\Delta X'$ but whites luminance level plane 893 and the blacks luminance level plane 891 remain stationary. However, all the other luminance planes are adjusted according to curve 895. Additional details on one implementation of the math behind these color adjustments will be presented later in this document.

Luminance Adjustment Sliders

Referring back to Figure 4, the graphical user interface further includes three luminance adjustment sliders 439, 429, and 419 associated with each of the three luminance planes illustrated in Figure 5. Specifically, Figure 4 illustrates whites luminance slider 439, mids luminance slider 429, and blacks luminance slider 419. The luminance adjustment sliders 439, 429, and 419 adjust the luminance levels of pixels on luminance plane 530, 520, and 510, respectively.

As with the color adjustment pads, the luminance sliders adjust the luminance on their respective luminance planes. The whites luminance slider 439 adjusts the luminance for the pixels on the whites luminance plane 530 and the remaining luminance planes as a function of how close those other planes are to the whites

5 luminance plane as illustrated by the input (x)/output (y) graphs in **Figure 13**. Specifically, moving the whites luminance adjustment slider 439 to the right increases the luminance of high luminance pixels as illustrated in **Figure 14(c)**. Similarly, moving the whites luminance adjustment slider 439 to the left lowers the luminance of high luminance pixels as illustrated in **Figure 14(d)**. Leaving the whites luminance adjustment slider 439 in the center leaves the high luminance pixels unchanged.

The blacks luminance slider 419 adjusts the luminance for the pixels on the blacks luminance plane 510 and the remaining luminance planes proportionally. Specifically, adjusting the blacks luminance slider 419 to the left decreases the luminance as illustrated by the input(x)/output(y) graphs of **Figure 14(a)** and adjusting the blacks luminance slider 419 to the right increases the luminance as illustrated in **Figure 14(b)**.

The mids luminance slider 429 adjusts the luminance of pixels on the mids luminance plane 520. In one embodiment, the adjustment to the mids luminance slider adjusts the other luminance planes in a curved manner according to a curve as illustrated in **Figures 14(e) and 14(f)**. Specifically, moving the mids luminance slider 429 to the right raises the luminance of the mids as illustrated in **Figure 14(e) and 14(g)** and moving the mids luminance slider 429 to the left lowers the luminance of the mids as illustrated in **Figure 14(g)**.

Auto-Contrast Buttons

In the center of the graphical user interface of **Figure 4** is a set of auto-contrast buttons **460**. The auto-contrast buttons **460** are used to analyze a frame of the image being manipulated and then automatically adjust the luminance of the image.

- 5 Specifically, the auto-contrast buttons **460** automatically adjust the blacks luminance slider **419** and whites luminance slider **439** to values which will expand or contract the luma values in the original images to fall into the maximum CCIR-recommended luma ranges (16 and 235).

10 Referring to the auto-contrast buttons **460** in **Figure 4**, the specific auto-contrast buttons from left to right are: auto-black-level, auto-contrast, auto-white-level. The Auto-black-Level button will adjust the blacks slider to make the lowest input luma value map to CCIR-black (16). The Auto-White-Level button will adjust the highest input luma value to map to a user-specified white value. This user-specified white value
15 is normally CCIR-white (235). The auto-contrast button performs both operations (auto-black-level and auto-white-level) in one step.

These auto-contrast buttons **460** are highly desirable since one of the tasks that professional colorists often perform is to adjust the black and white levels to see what
20 contrast the original image has. After seeing the contrast in the original image, the colorist may increase (or decrease) the image's contrast as appropriate.

Saturation Adjustment Slider

- 25 Referring again to **Figure 4**, a saturation adjustment slider **450** can be used to adjust the saturation of all the pixels. The saturation adjustment slider **450** adjusts the

saturation of the effected pixels by multiplying each pixel's current saturation value with a saturation multiplier value between zero and two.

Adjusting the saturation with a saturation multiplier value of zero would change all the pixels to zero saturation, resulting in a Black and white image. Adjusting the saturation with a saturation multiplier value of two would double the saturation of each pixel. Leaving the saturation adjustment slider **450** in the center position multiplies the saturation by a value of one and thus does not change the saturation of the pixels.

Limit Effect Panel

To limit the effects of color correction, the user may define a limited three-dimensional space within the three-dimensional colorspace that should be adjusted.

Referring to **Figure 4**, the "limit effect" panel **460** at the bottom of the graphical user interface allows the user to specify a limited volume within the colorspace by selecting a particular hue range, saturation range, and luminance (luma) range. Limiting the effected pixels is also known as "keying."

Referring back to the colorspace illustration of **Figure 1(b)**, an example of a defined three-dimensional space **150** within the three-dimensional colorspace is illustrated. Three-dimensional space **150** is defined with a Δy luminance range, a Δs saturation range, and a Δh hue angle range. Not all three parameters need to be specified. If a particular parameter is not specified, then the entire range of that parameter will be adjusted with the color corrections. If no parameter is specified, then all the pixels will be effected.

Referring back to the limit effect panel **460** of **Figure 4**, a user may specify a Δh hue angle range by marking the hue angle range checkbox **478** (which indicates that the Δh hue angle range should be considered) and defining a hue angle range on the hue spectrum **470**. The Δh hue angle range is specified along a hue spectrum **470** using a pair of defining hue markers **471** and **472**.

The angle determined by the defining hue markers **471** and **472** is used to allow the user to generate a smooth falloff for the color effect. For colors completely inside the defining hue markers **471** and **472**, the effect is applied 100%. For colors completely outside the defining hue markers **471** and **472**, the effect is not applied. For colors that fall into the “falloff area” which the user specifies by the angle of the defining hue markers **471** and **472**, the resulting pixel is calculated by blending the original, unmodified pixel with the pixel after the effect has been applied. The effect is proportional to where the original pixel color is in the falloff area. Thus, the angled defining hue markers **471** and **472** allows for a smooth gradation between pixels subject to the effect and pixels not subject to the effect.

The user may press hue angle reset button **477** to reset the defined hue angle to a default hue angle. In one embodiment, the default hue angle is -110° with a default width of 15° and a default softness of 10. The user may center the hue spectrum **470** on a particular hue by selecting a hue from the image using eyedropper button **474**.

A user may specify a Δs saturation range by marking the saturation range checkbox **488** and defining a saturation range on the saturation scale **480**. The Δs saturation range is specified along the saturation scale **480** using a pair of defining

saturation markers **481** and **482**. As set forth with reference to the defining hue markers **471** and **472**, the angle determined by the defining saturation markers **481** and **482** is used to allow the user to generate a smooth falloff for the color correction. The user may press saturation range reset button **487** to reset the defined saturation range to a default

5 saturation range. In one embodiment, the default saturation range starts at 35% with a width of 40 and a softness of 20. The user may center the saturation markers **481** and **482** around a particular pixel's saturation value by selecting a pixel from the image using eyedropper button **474**.

10 Finally, a user may specify a Δy luminance range by marking the luminance range checkbox **498** and defining a luminance range on the luminance scale **490**. The Δy luminance range is specified along the luminance scale **490** using a pair of defining luminance markers **491** and **492**. As set forth with reference to the defining hue markers **471** and **472**, the angle determined by the defining luminance markers **491** and **492** is used to allow the user to generate a smooth falloff for the color correction. The user may press luminance range reset button **497** to reset the defined luminance range to a default luminance range. In one embodiment, the default luminance range starts at 0% with a width of 40 and a softness of 20. The user may center the luminance markers **491** and **492** around a particular pixel's luminance value by selecting a pixel from the image using eyedropper button **474**. Furthermore, if the user activates the eyedropper while holding the shift key down then the hue, saturation, or luminance on which the user clicks will be added to the keying selection.

Alternative Color Correction Graphical User Interfaces

The graphical user interface for the color correction window may be implemented in many different manners. The different color correction graphical user interface embodiments may include new features and omit other features.

Figure 9 illustrates a first alternate embodiment of a color correction user interface. In the embodiment of **Figure 9**, there is only a single color adjustment pad **910** for adjusting the whites luminance plane **530** as illustrated in **Figure 5**. Thus, in the embodiment of **Figure 9**, only the whites luminance plane **630** may be adjusted as illustrated in **Figure 6(a)**. However, the embodiment of **Figure 9** includes all three luminance adjustment sliders **939**, **929**, and **919** such that the luminance levels of all three different luminance planes **530**, **520**, and **510** may be adjusted accordingly.

Hue Phase Shift Adjustment

The color correction embodiment of **Figure 9** introduces a new color adjustment device, the hue adjustment wheel **920**. The hue adjustment wheel **920** allows the user to simultaneously adjust the hues of all the pixels (defined by the limit effect panel) by rotating the colorspace. Specifically, a user may rotate the outer wheel **921** to rotate the hue spectrum. This causes the entire colorspace to be rotated by a corresponding amount as illustrated by the arrow **521** in **Figure 5**. This type of color change is sometimes known as a hue phase shift. To reset any hue phase shift changes, the user may activate the hue rotation reset button **527** to move the hues back to their original (default) position.

Figure 10 illustrates a second alternate embodiment of a color correction user interface. In the embodiment of **Figure 10**, there are three color adjustment pads **1010**, **1020**, and **1030** as well as a hue adjustment wheel for adjusting the hues in a colorspace. The color correction user interface of **Figure 10** is very powerful since it contains all the features of the previous two user interfaces, but the color correction user interface of **Figure 10** is slightly cluttered.

Color Correction Implementation

The present invention provides for color correction in a novel manner by performing the color correction and keying in the YUV colorspace in order to reduce processing cycles and to save time through the avoidance of rendering. This is in marked contrast to prior art techniques that perform color correction in the RGB space and, thus, tend to involve greater amounts of rendering. By reducing or removing the time consuming rendering steps, the system of present invention is more efficient than prior art systems.

As will be described more fully in the sections hereafter, the inventive techniques utilize look-up tables (LUTs) that may convert user inputted color corrections to the YUV or YCrCb colorspace in selected images to an outputted value. Although YUV and YCrCb denote different values mathematically, for purposes of the present invention, YUV and YCrCb are deemed interchangeable as used herein. The look-up tables (LUTs) that provide for the remapping of pixels according to the user's desired color correction are used to provide a high performance pixel remapping. However, the

color correction pixel remapping performed by the present invention may be implemented in other manners.

To fully describe the implementation of all the different features, the implementation will be described with reference to the color correction graphical user interface of **Figure 10**. The color correction graphical user interface of **Figure 10** includes user interface devices for adjustment of color space shifting, hue phase shift, luminance levels, and saturation.

Figure 11 illustrates a flow diagram containing, a segment of the inventive technique in one embodiment. User input representing the desired color correction is received at **1110** for a given color space. The user input may be provided using of the graphical user interfaces depicted in **Figures 4, 9, or 10**. In one embodiment, the user input from the color adjustment pads may be in the form of a vector that is converted at **1120** to Cartesian coordinates for computational purposes. In another embodiment, however, it is possible to have the user input directly in the form of Cartesian coordinates, without the use of vectors.

Once Cartesian coordinates form, a recomputation of the applicable look-up tables (LUTs) is performed at **1130**, the details of which will be discussed in greater detail below. Note that in certain applications, however, it may not be necessary to recomputed one or more LUTs, given that it is possible that a user may only modify a parameter that does not require a look-up table recomputation such as a saturation adjustment. Finally, the color information of designated pixels are remapped at step

1140. In one embodiment, the YCrCb values that define the designated pixels are remapped with the aid of the recomputed from the look-up tables (LUTs).

Figure 12 illustrates a flow diagram describing the pixel remapping referred to in step 1140 of Figure 11. The pixel color correction may begin by receiving a pixel at step 1210.

Based on user input from the previously described luminance adjustment sliders, an adjustment to the pixel's luminance is made at step 1220 based on the luminance look-up tables (LUTs), as described in greater detail hereafter. Specifically, the luminance (Y) of a pixel is set with the following equation:

$$Y = yLUT(Y) \text{ where } Y \text{ is the pixel's luminance value}$$

As such, the previously described luminance adjustment sliders are able to provide user control of the luminance (Y) value of a YCrCb defined pixel.

Next, an adjustment to the chrominance is made at 1230 based on the chrominance look-up tables (LUTs) that have been modified based on user input from the color adjustment pads as previously disclosed. Note that the chrominance adjustment is relative to the initial chrominance value. The chrominance values are adjusted with the following equations:

$$\begin{aligned} Cb &= Cb + \text{signedCbLUT}(Y); \text{ and} \\ Cr &= Cr + \text{signedCrLUT}(Y) \text{ where } Y \text{ is the pixel's luminance value} \end{aligned}$$

As such, the previously described color adjustment pads are able to provide user control of the chrominance (Cr and Cb) values of a YCrCb defined pixel.

Also as previously described, the color correction user interface may include a hue adjustment wheel that may rotate the hues of pixels. The hue rotation may

be expressed as a phase shift h . In accordance with one embodiment, a final assignment of chrominance is made, based on any existing phase shift h , at step 1240. The phase shifted chrominance values are determined from the previous chrominance values and the phase shift h . The general equations for this determination are:

5
$$\begin{aligned} C_b &= C_b * \cos(h) - C_b * \sin(h); \text{ and} \\ C_r &= C_r * \cos(h) - C_r * \sin(h). \end{aligned}$$

In systems without a hue adjustment wheel for phase modification h , there would be no need for step 1240 of Figure 12.

10 A final adjustment is made to a pixel's C_r and C_b values at step 1250, based on a saturation adjustment s . The saturation adjustment s (or satadjust) may increase or decrease the amount of color depending on user input using the saturation adjustment slider. This increase or decrease is accomplished by setting the saturation adjustment s to a value between 0 and 2 inclusive and then multiplying the above final
15 color correction results by the factor of s to get the final adjusted color correction. Specifically, the following equation may be used to implement saturation adjustments to the pixels:

$$\begin{aligned} C_b &= 128 + (\text{satadjust} * (C_b - 128)); \text{ and} \\ C_r &= 128 + (\text{satadjust} * (C_r - 128)) \end{aligned}$$

20 Although it is possible to use other s values beyond the range of 0 and 2, such values tend to have little utility, given that the extremes of 0 to 2 represent the mainstream uses of color, where 0 represents no saturation, and 2 represents double the normal saturation for any given color.

25 Steps 1210 through 1250 are then repeated until the last pixel from the designated image(s) has been remapped, as determined at 1260.

Luminance Correction: LUT Recomputations

As set forth in the flow diagram of **Figure 12**, the first pixel adjustment in one embodiment of the present invention is to adjust the pixel's luminance (Y) value.

- 5 The adjusted luminance value is based on the pixel's current luminance value and input from the user on the luminance sliders in the graphical user interface. The user input is used to adjust a luminance look up table that will be used to modify the luminance of each affected pixel.

10 **Figure 13** illustrates a graphical representation of the potential transitions for the relationship between the different pixel luminance input values on the input (x) axis **1305** versus the respective pixel luminance output values on the output (y) axis **1310**. As previously set forth, a user may adjust the luminance adjustment sliders in order to modify luminance control values W , M , and B .

15 The changes of in the luminance control values W , M , and B adjust the input/output graph as set forth in **Figure 13**. Specifically, changes to the W luminance control value may adjust the input/output graph in the directions indicated at **1320**, changes to the M luminance control value may adjust the input/output graph in the
20 directions indicated at **1330**, and changes to the B luminance control value may adjust the input/output graph in the directions indicated at **1340**.

Figures 14(a) to 14(g) illustrate more specific examples which are controlled for movement of individual variables in accordance with the previously
25 described user interface. Specifically: **Figure 14(a)** illustrates the resulting input/output

graph where the *B* value has been made darker, as seen by the movement of the *B* from the origin point out along the *x* axis; **Figure 14(b)** illustrates the resulting input/output graph where the *B* value has been made lighter, as seen by the movement of the *B* from the origin point out along the *y* axis; **Figure 14(c)** illustrates the resulting input/output graph where the *W* value has been made lighter, as seen by the movement of the *W* back along the *x* axis; **Figure 14(d)** illustrates the resulting input/output graph where the White *W* value has been made darker, as seen by the movement of the *W* down along the *y* axis; **Figure 14(e)** illustrates the resulting curved input/output graph where the *M* value has been lifted up, as seen by the movement of the *M* in an upward direction; **Figure 14(f)** illustrates the resulting curved input/output graph where the *M* value has been moved down, as seen by the movement of the *M* in a downward direction. It is significant to note that **Figures 14(e) and 14(f)** differ markedly from **Figures 14(a) to 14(d)** in that the input/output relationship of the latter is marked by a straight line (and hence, is computed according to a general linear equation such as $y = mx + b$), while the input/output relationship of the former is computed by any non-linear equation as known in the art of curve computation, such as a Bezier function.

Although there are other techniques that would yield similar curves using different mathematical approaches, in one embodiment, a Bezier function is utilized.

Accordingly, **Figure 14(g)** details, for one embodiment, the usage of an exemplary Bezier curve 1490 and the control points k0 1410, k1 1460, k2 1480 and k3 1440 of the Bezier curve function which are used to compute the non-linear input/output relationship on the look-up table which correlate to *M* control modifications. More specifically, the Bezier control points k0 1410, k1 1460, k2 1480 and k3 1440 for the luminance map are set up based on the endpoints and the previously described *M* adjustment slider.

In one embodiment, the curve for the *M* control is calculated using Bezier control points k0 1410, k1 1460, k2 1480 and k3 1440. The endpoints k0 1410 and k3 1440 for the Bezier curve are calculated the same way as they would be for a linear case, as shown in Figures 14(a) to 14(d), and are derived solely from the blacks luminance slider 419 and whites luminance slider 439 of Figure 4. MidPt 1430, Corner 1450, and CtlPt 1470 are all intermediate values used to illustrate how k1 1460 and k2 1480 are derived from k0 1410, k3 1440, and the previously described *M* adjustment slider, the middle Bezier control points (k1 1460, k2 1480) are calculated as follows.

First, a calculation is made for the midpoint between k0 1410 and k3 1440.

Specifically:

$$\text{MidPt.h} = \frac{(k0.h + k3.h)}{2}$$

A similar expression may be likewise employed for midPt.v. Next, a choice is made designating either the upper left or lower right, depending on the direction *M* is being pushed, such that:

If *M* < 100, lower right, then Corner.h = k3.h and Corner.v = k0.v
Else if *M* > 100, upper left, then Corner.h = k0.h and Corner.v = k3.v.

Next, a calculation is made as to how far out to go on the line between MidPt 1430 and Corner 1450. Specifically, CtlPt 1470 is interpolated by using a weighting derived from weight = abs((mids-100)/100.0) where the larger the *M* ("mids") value, the more influence that Corner 1470 will have. Conversely, the smaller the value, the less influence Corner 1470 will have, e.g.:

$$\text{CtlPt.h} = \text{weight} * \text{Corner.h} + (1.0 - \text{weight}) * \text{MidPt.h}$$

A similar expression may be employed to obtain CtlPt.v.

Next, a calculation is made to determine k1 1460, by interpolating between k0 1410 and CtlPt 1470, again using the above-described weighting factor:

$$k1.h = \left(\frac{0.5 + (1.0 - weight)}{2} \right) * CtlPt.h + \left(\frac{1.0 - 0.5 + (1.0 - weight)}{2} \right) * k0.h$$

A similar expression may be employed to obtain k1.v.

5

Likewise, a calculation is made to determine k2 at 1480:

$$k1.h = \left(\frac{0.5 + (1.0 - weight)}{2} \right) * CtlPt.h + \left(\frac{1.0 - 0.5 + (1.0 - weight)}{2} \right) * k3.h$$

A similar expression may be employed to obtain k2.v.

Figure 14(g) illustrates where these points would lie relative to k0 1410 and k3 1440 for $M > 100$. As M (and therefore the above described “weight”) is changed, CtlPt will be interpolated to different locations along the line between Corner 1450 and MidPt 1430. Furthermore, k1 1460 and k2 1480 will be interpolated to different positions on the lines between k0 1410 and CtlPt 1470 and between k3 1440 and CtlPt 1470. The arrows at k1 1460, CtlPt 1470, and k2 1480 suggest how these points move as the mids (M) luminance slider is adjusted (in the range 100-200).

Note that if $M < 100$, then the lower right corner of the bounding box formed by (k0, k3) would be used as Corner, and the curve would then inflect in the other direction, but otherwise, the relative positioning of the points (based on “weight”) is the same. If, however, M was set to 100, the graph would instead be a straight line as shown in Figure 14(a) to 14(d).

Chrominance (U and V) Correction: LUT Recomputations

As discussed with reference to Figure 12, the second adjustment in one embodiment of the present invention is a pixel chrominance adjustment based on input

from the user on the color adjustment pads. Adjustments to the color adjustment pads skew the three-dimensional color space such that the chrominance value for each pixel must be changed. For example, **Figure 6(b)** illustrates how the three-dimensional colorspace is adjusted when the user moves the center of the blacks color adjustment pad **410** to the right by an amount ΔX . In mathematical terms, the effect of an adjustment of ΔX to the whites (W) luminance plane or blacks (B) luminance plane on the mids (M) luminance plane would be that of $\frac{\Delta x}{2}$ for a movement of Δx by *W* or *B*, as depicted in

Figures 6(a) and 6(b). An adjustment to the mids (M) luminance plane would affect the cylindrical representation along the Bezier shaped luminance axis (Y) as broadly depicted in **Figure 7**, and as will be more fully detailed in the below exemplary applications.

When a user makes adjustments to a color adjustment pad, the user's input may be received as an angle and magnitude defined vector. The angle and magnitude defined vector is then translated into a relative U,V vector for that luminance plane. For example, referring to **Figure 5**, a vector input for the white color adjustment pad would be translated into a Cartesian vector with a U_W value specifying a relative move along the U-axis and a V_W value specifying a relative move along the V-axis. Thus, for the example of **Figure 6(a)**, the relative Cartesian vector would be $U_W = \Delta X$ and $V_W = 0$.

To convert an angle vector push defined by magnitude m and an angle α , the Cartesian vector U and V can be found according to the generalized equations:

$$\begin{aligned} U_W &= m_W * \sin \alpha_W & V_W &= m_W * \cos \alpha_W \\ U_M &= m_M * \sin \alpha_M & V_M &= m_M * \cos \alpha_M \\ U_B &= m_B * \sin \alpha_B & V_B &= m_B * \cos \alpha_B \end{aligned}$$

Figure 15 illustrates an unchanged cylindrical colorspace representation where the white (W), mid (M), and black (B) luminance planes are physically centered on the $C_b = 0, C_r = 0$ axis. Thus, in **Figure 15**, all of the relative Cartesian vector values $U_W, V_W, U_M, V_M, U_B, V_B$ are zero. In **Figure 15**, the C_b look-up table (CbLUT) and the

5 C_r look-up table (CrLUT) are both of the form $y = 0$, a constant of zero. Applying the functions CbLUT and CrLUT, for any luminance value, the result is always

CbLUT[luminance] = 0.0 and CrLUT[luminance] = 0.0.

Figure 16 illustrates another example of the cylindrical colorspace

10 representation where the white (W), mid (M), and black (B) luminance planes have all been shifted such that each has been pushed an equal amount to reflect different amounts of C_b and C_r values. As in the previous diagram, the vertical line in **Figure 16** is centered on the $C_b = 0, C_r = 0$ location for all three luminance planes. In **Figure 16**, C_b has been pushed by -0.30 and C_r has been pushed by 0.10 . Thus, CbLUT and CrLUT

15 are both of the form $y = C$ (e.g., a constant) given that the same amount of push is applied to C_b and C_r regardless of luminance. Specifically, for all luminance values,

CbLUT[luminance] = -0.30 and CrLUT[luminance] = 0.10 .

Figure 17 illustrates a more complex example of adjusting the cylindrical

20 colorspace representation where the white, mid, and black luminance planes are being pushed differently. To interpolate the adjustments for the luminance planes in between the white, mid, and black luminance planes, a Bezier curve is used. Although this implementation uses a Bezier function to generate a curve that users have found to be appropriate for the given color correction, other functions that generate similar curves and

25 even other curves may also be used.

Figure 18 illustrates a graph **1894** created from two Bezier curves connected by a linear segment (between **1890** and **1880**), with theoretical control points (**1810**, **1820**, **1890**, and **1892**) and (**1880**, **1870**, **1840**, and **1850**). Utilizing the graph

5 **1894** created from two Bezier curves connected by the linear segment, a more specific instantiation may be arrived at such as in **Figure 19**, where the graph created from two Bezier curves and the linear segment is termed “gMidRamp”. The gMidRamp, as detailed in the below mathematic equations, is used to generate look up table for Cb, (CbLUT) as illustrated in **Figure 20** and a look-up table for Cr (not shown).

Referring back to **Figure 18**, the Bezier control points for gMidRamp may accordingly be derived where the detailed control points assume that luma = 0 corresponds to CCIR-black and luma = 219 corresponds to CCIR-white (and values above 219 are superwhite). Additional assumptions in this illustrative case are such that:

15 (1) the lookup table size is assumed to be 256; (2) the lookup table is pre-initialized below 55 with 0 and above 164 with 0; (3) the lookup table is pre-initialized between 55 and 164 with 1.0; (4) the Bezier curves are placed with a left endpoint (0,0) at array index 4 (**1810**) and right endpoint (1.0, 1.0) at array index 104 (**1890**), and control points of (0.25, 0.0) (**1820**) and (0.75, 1.0) (**1892**), as shown at left side of **Figure 18**; and (5) the

20 curves are further placed with a left endpoint (0.0, 1.0) at array index 114 and a right endpoint (1.0, 0.0) at array index 214 (**1850**), and control points of (0.25, 1.0) (**1880**) and (0.75, 0.0) (**1840**), as at right. Hence, from left to right, the circles are control pts k0, k1, k2, k3, and k0, k1, k2, k3. The graph starts at 0, and tick marks represent 50% luma (114.5) and CCIR-white (219) (**1860**).

Referring back to **Figure 17**, the relative Cartesian vectors (U_W , V_W) and (U_B , V_B) are generated directly from the user's inputs to the white and black color adjustment pads. However, the Cartesian vector for the mids (M) luminance plane is a combination of the user input for the blacks and whites luminance planes along with the user's direct input for the mids luminance plane. Specifically, the Cartesian vector for the mids luminance plane (U'_M , V'_M) is generated with:

$$U'_M = \frac{U_W + U_B}{2} + U_M$$

$$V'_M = \frac{V_W + V_B}{2} + V_M$$

where U_M and V_M represent the user's directly specified offset for the mids luminance plane.

Accordingly, to generate the needed Cb look-up table (CbLUT) of **Figure 20**, the following equations are used:

for $i < 50\%$ White (CCIR luminance value of 128) then

$$CbLUT[i] = U_B * (1.0 - gMidRamp[i]) + U'_M * (gMidRamp[i])$$

for $i \geq 50\%$ White (CCIR luminance value of 128) then

$$CbLUT[i] = U_W * (1.0 - gMidRamp[i]) + U'_M * (gMidRamp[i])$$

Thus, **Figure 20** illustrates the CbLUT function in this example where Cb is pushed a small negative amount on the mids luminance plane (M) (say, approximately -0.3) but has not been pushed at all on the blacks or whites luminance planes. In this example, Cr is not being pushed at all (No plane has been moved in the V direction) such that $CrLUT[i] = 0$ for all values of i .

Figure 21 illustrates another example of a modified cylindrical colorspace representation. In the modified the cylindrical colorspace representation of **Figure 21**, both the mids and the white luminance planes have been pushed. In this case, the same

techniques are used to create the chrominance look-up tables (CbLUT and CrLUT). Note the same gMidRamp function is used.

In the modified cylindrical colorspace representation of **Figure 21**, both Cb and Cr are being pushed at the mids (M) luminance plane and only Cb is being pushed at whites (W) luminance plane. Thus, the effect of mids and whites luminance plane adjustments on Cb (from the mids and whites color adjustment pads) can be seen in graph of the Cb look-up table (CbLUT) in **Figure 22** at the mid luminance levels and at the high (white) luminance levels. Referring to **Figure 23**, since Cr has only been pushed at the mids luminance plane, the Cr look-up table (CrLUT) is symmetric about the mid luminance level.

Keying To Limit Effects

In one embodiment, keying may be employed to limit the effect of color correction. **Figure 24** illustrates a broad description of the inventive color correction system according to the recomputation of YUV values by usage of look up tables as described for a keyed area. As indicated at **2405**, the first step and differentiating step from the process outlined in **Figure 11** involves identifying a keyed color region.

Generally speaking, the techniques of keying may be used to identify or designate an entire image or images, as well as specific portions thereof, or even may be applied to specific object or backgrounds, as known in the art of keying. Additionally, the key may be partial (semi transparent) in which case the color corrected result is mixed with the uncorrected (original) pixel, allowing for a smooth transition between corrected and uncorrected areas of the images when using the Limit Effect panel. In one embodiment, keying is performed using the limit effect panel **460** of **Figure 4**.

Figure 25 illustrates an overall description of the pixel remapping of the inventive color correction described in **Figure 12** but only over the keyed pixels. As indicated, the differentiating step for keying over a designated area occur at **2515**, where an assessment is made as to whether a pixel having color value YCrCb is in a keyed area.

5

The foregoing has described a method and user interface for performing color correction. It is contemplated that changes and modifications may be made by one of ordinary skill in the art, to the materials and arrangements of elements of the present invention without departing from the scope of the invention.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204